

Fog Fury Jett		1 Channel Mode
Channel	Value	Function
1	0 - 15 16 - 31 32 - 255	FOG & RANDOM COLOR CHANGE OFF COLOR MACRO PREVIEW MAX FOG & COLOR CHANGE

The color macro preview will a run a 5 second random LED show. This show will repeat every 15 seconds.

Fog Fury Jett		2 Channel Mode
Channel	Value	Function
1	0 - 15 16 - 31 32 - 255	FOG & RANDOM COLOR CHANGE OFF COLOR MACRO PREVIEW MAX FOG & COLOR CHANGE
2	0 - 255	COLOR MACROS Please see page 15 for Color Macros

The color macro preview will a run a 5 second random LED show. This show will repeat every 15 seconds. You can use the color macro preview with the color macro mode (channel 2). By adjusting the color macros the color macro preview will show you the current color macro that the fader is set to. This color macro will be the color macro that is seen when there is fog output.

Fog Fury Jett		3 Channel Mode
Channel	Value	Function
1	0 - 15 16 - 31 32 - 255	FOG & RANDOM COLOR CHANGE OFF COLOR MACRO PREVIEW MAX FOG & COLOR CHANGE
2	0 - 255	COLOR MACROS Please see page 15 for Color Macros
3	0 - 31 32 - 95 96 - 159 160 - 255	STROBING OFF STROBING SLOW - FAST PULSE EFFECT RANDOM STROBE SLOW - FAST

Color Macros/RGBA will not work unless fog is active.

Fog Fury Jett		5 Channel Mode
Channel	Value	Function
1	0 - 15 16 - 31 32 - 255	FOG & RANDOM COLOR CHANGE OFF COLOR MACRO PREVIEW MAX FOG & COLOR CHANGE
2	0 - 255	RED 0% - 100%
3	0 - 255	GREEN 0% - 100%
4	0 - 255	BLUE 0% - 100%
5	0 - 255	AMBER 0% - 100%
Fog Fury Jett		7 Channel Mode
Channel	Value	Function
1	0 - 15 16 - 31 32 - 255	FOG & RANDOM COLOR CHANGE OFF COLOR MACRO PREVIEW MAX FOG & COLOR CHANGE
2	0 - 255	RED 0% - 100%
3	0 - 255	GREEN 0% - 100%
4	0 - 255	BLUE 0% - 100%
5	0 - 255	AMBER 0% - 100%
6	0 - 31 32 - 95 96 - 159 160 - 255	STROBING OFF STROBING SLOW - FAST PULSE EFFECT RANDOM STROBE SLOW - FAST
7	0 - 255	MASTER DIMMER 0% - 100%

Color Macros/RGBA will not work unless fog is active.