

## ELIMINATOR COSMIC BURST - DMX TRAITS

CHANNEL		DMX VALUES	FUNCTION
1	1		<b><i>Reflector Rotation</i></b>
		000 - 007	Standby
		008 - 125	Clockwise Rotation, fast to slow
		126 - 129	Stop
		130 - 247	Counter-Clockwise Rotation, slow to fast
		248 - 255	Stop
2	2		<b><i>Shutter, Strobe</i></b>
		000 - 031	Off
		032 - 063	On
		064 - 095	Strobe Effect, slow to fast
		096 - 127	On
		128 - 159	Pulse Effect in Sequences
		160 - 191	On
		192 - 223	Random Strobe Effect, slow to fast
224 - 255	On		
3	3	000 - 255	<b><i>Dimmer Intensity</i></b> , 0% to 100%
	4	000 - 255	<b><i>Dimmer Fine</i></b>
4	5		<b><i>Effect</i></b>
		000 - 008	Stop
		009 - 015	Open
		016 - 255	Shutter, slow to fast
5	6		<b><i>Show</i></b>
		000 - 045	Null
		046 - 087	Show 1
		088 - 129	Show 2
		130 - 171	Show 3
		172 - 213	Show 4
		214 - 255	Show 0 (Random Show 1-4)
6	7	000 - 255	<b><i>Speed</i></b> , slow to fast